

Stückliste CPS8256-Clone

ID:	Bezeichner:	Stückzahl:	Bezeichnung:	Anbieter:	Referenz:	Footprint:
1	C1, C2, C3, C4, C5, C6, C9	7	100nF	ebay	Kondensator	C_Disc_D4.3mm_W1.9mm_P5.00mm
2	C7, C8, C10, C11	4	1uF	ebay	Kondensator	C_Disc_D4.3mm_W1.9mm_P5.00mm
3	D1	1	PWR-LED	ebay	Signalanzeige	LED_D5.0mm
4	D2	1	DCD act. LED	ebay	Signalanzeige	LED_D3.0mm
5	D3, D4, D5, D7	4	1N4148	ebay	Si-Diode	D_DO-41_SOD81_P10.16mm_Horizontal
6	D6	1	RX/TX-LED	ebay	Signalanzeige	LED_D5.0mm
7	H1	1	PAD-Masse	ebay	Masse Test-Punkt	TestPoint_Loop_D2.50mm_Drill1.0mm
8	J1	1	2x25-Pin Centr-Stecker JOYCE-Systembus	Kessler-Electronic	CES50PR, Art.-Nr.: 606425;0	50-PIN-CENTRONICS-M 90° für PCB-Montage
9	J2	1	RS232-Port	ebay	PinHeader_2x05	PinHeader_2x05_P2.54mm_Vertical
10	J3	1	Centronics-Port	ebay	PinHeader_2x05	PinHeader_2x08_P2.54mm_Vertical
11	Q1	1	2N3904	ebay	Si-Transistor	TO-92L
12	Q2	1	BC557	ebay	Si-Transistor	TO-92L
13	R1	1	2k2	ebay	Metallsch. 1%/0,25W	R_Axial_DIN0207_L6.3mm_D2.5mm_P10.16mm_Horizontal
14	R2	1	10k	ebay	Metallsch. 1%/0,25W	R_Axial_DIN0207_L6.3mm_D2.5mm_P10.16mm_Horizontal
15	R3, R4, R5	3	2k2	ebay	Metallsch. 1%/0,25W	R_Axial_DIN0411_L9.9mm_D3.6mm_P12.70mm_Horizontal
16	R6	1	1k5	ebay	Metallsch. 1%/0,25W	R_Axial_DIN0207_L6.3mm_D2.5mm_P10.16mm_Horizontal
17	R7, R8	2	10k0	ebay	Metallsch. 1%/0,25W	R_Axial_DIN0207_L6.3mm_D2.5mm_P10.16mm_Horizontal
18	R9	1	47k0	ebay	Metallsch. 1%/0,25W	R_Axial_DIN0411_L9.9mm_D3.6mm_P12.70mm_Horizontal
19	R10	1	150R	ebay	Metallsch. 1%/0,25W	R_Axial_DIN0207_L6.3mm_D2.5mm_P10.16mm_Horizontal
20	U1	1	74LS32	ebay	TTL-IC	DIP-14_W7.62mm_LongPads
21	U2	1	74LS00	ebay	TTL-IC	DIP-14_W7.62mm_Socket_LongPads
22	U3	1	74LS138	ebay	TTL-IC	DIP-16_W7.62mm_LongPads
23	U4	1	8254-CTC	ebay	TTL-IC	DIP-24_W15.24mm_LongPads
24	U5	1	74LS74	ebay	TTL-IC	DIP-14_W7.62mm_LongPads
25	U6	1	Z80DART	ebay	TTL-IC	DIP-40_W15.24mm_Socket_LongPads
26	U7	1	MAX232	ebay	TTL-IC	DIP-16_W7.62mm_LongPads
27	U8	1	74LS373	ebay	TTL-IC	DIP-20_W7.62mm_LongPads
28	PCB	1	PCB	Aisler o. ä.	Leiterplatte	CPS8256-Clone
29	DIL-14	3	IC-Sockel	ebay	IC-Sockel	
30	DIL-16	2	IC-Sockel	ebay	IC-Sockel	
31	DIL-20	1	IC-Sockel	ebay	IC-Sockel	
32	DIL-24	1	IC-Sockel	ebay	IC-Sockel	
33	DIL-40	1	IC-Sockel	ebay	IC-Sockel	
34						

Pos. 8:

